

単線(A)

公称サイズ AWGサイズ	構成 (本/mm)	20°Cにおける導体抵抗 (Ω/km)標準値導電率=100%	計算 断面積 (mm ²)
30	1/0.26 A	331.3	0.053
28	1/0.33 A	205.7	0.085
26	1/0.42 A	127.0	0.138
24	1/0.52 A	81.8	0.212
22	1/0.65 A	52.3	0.332
20	1/0.83 A	32.1	0.541
18	1/1.04 A	20.3	0.849
16	1/1.30 A	13.0	1.327
14	1/1.65 A	8.1	2.137
12	1/2.10 A	5.0	3.462
10	1/2.60 A	3.2	5.307